

Kwik Lite

Features

- LESS POWER MORE LIGHT
- POWER SAVING – 10%
- INCREASED LAMP LIFE
- WORKS FROM 140V - 280V
- CAN BE USED IN SV & MH

Technical Specifications

Model	KEPS HID 400W
Lamp Wattage	400W
Power Consumption	410W
Mains Current	1.78 Amps
Power Factor	0.96
Ballast Loss	10W (Approx.)
Supply	240V AC & DC
Functioning at low temp.	minus 10 deg. C
Noise Level	NIL
Stroboscopic effect	Absent
Protection	Built-in fuse Deactivated Lamp Sensing Abnormal Wattage Sensing Open Circuit Sensing
Ignitor	Not required
Power Factor Capacitor	Not required
Auto restart	Provided
Temperature rise	10-15 deg. C above ambient
Crest Factor	< 1.95
THD	< 30%
Operating Frequency	greater than 20 KHz.
Dimensions	220x135x75 mm
Weight	Approx. 1300 gms



Kwiklite Model No : KEPS HID 400W

Clients for KEPS HID 400W

- **Northeast Frontier Railway**
- **Penna Cement**
- **Granuel India**
- **Priya Cement**
- **NMDC**
- **Kesoram Cement**
- **Kesoram Cement**
- **Dept. of Light Houses & Light Ships,**
- **Cochin**
- **Chennai**
- **Mumbai**
- **Jam Nagar**
- **Goa etc.,**
- **Dept. Of Space**
- **Taj Group of Hotels**
- **Sigma Search Light Ltd.,**
- **Indian Oil Corporation**
- **K-Lite Industries**
- **Singareni Collieries**
- **Wheels India Ltd**
- **Dr.Reddy's Laboratories**

..... and more